



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 0 725 549 A2

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
07.08.1996 Bulletin 1996/32

(51) Int Cl.⁶: H04Q 7/22

(21) Application number: 96300653.1

(22) Date of filing: 30.01.1996

(84) Designated Contracting States:
DE FR GB SE

- Maeda, Ichiro
Tama-shi (JP)
- Fukushima, Takao
Hanno-shi (JP)

(30) Priority: 02.02.1995 JP 15928/95

(71) Applicant: HITACHI DENSHI KABUSHIKI KAISHA
Chiyoda-ku, Tokyo 101 (JP)


(74) Representative: Hackney, Nigel John et al
Mewburn Ellis,
York House,
23 Kingsway
London WC2B 6HP (GB)

(72) Inventors:
• Niki, Atsuyoshi
Koganei-shi (JP)

(54) Group-calls in a multi-channel access communication system

(57) A method of calling a terminal of a multi-channel access communication system having a plurality of terminals (4-1, 4-2) connected to communication channels. The plurality of terminals are classified into a plurality of groups each including at least one terminal. When a group calls another group, it is checked by referring to a management table (Figs. 1A & 1B) if there is any terminal in communications in the called group. If there is a terminal in communications, the call is invalidated.

FIG.6



Best Available Copy

EP 0 725 549 A2

Description

The present invention relates to a communication system of multi-channel access.

In a communication system of multi-channel access (hereinafter called MCA system), a plurality of communication channels are shared by a plurality of users. One example of MCA systems is an MCA/C (Multi-Channel Access on Cable) system. The MCA/C system provides users with telephone and facsimile services in addition to television broadcasting services, in a bi-directional CATV system.

According to the standard allocation of a carrier signal in an MCA/C system, a frequency bandwidth of 6 MHz per one channel is assigned for one television broadcasting signal inclusive of a video signal and a voice signal. A plurality of television broadcasting channels are distributed over the frequency band usable by each CATV system.

In the CATV system, a line for transmitting a signal from a subscriber terminal to a base station called a head end is called an "up-line", and a line for transmitting a signal from the head end to a subscriber terminal is called a "down-line". Different frequencies are used at the up- and down-lines.

Telephone services use a vacant frequency band in the CATV broadcasting band not used by television broadcast. The frequency band assigned to telephone and facsimile communications is 6 MHz per one channel of each up- or down-line. The MCA/C system has been proposed by "Survey and Study Group for Propagation and Promotion of Highly Integrated Information and Communication Systems" at the Ministry of Posts and Telecommunications in Japan.

Telephone services are offered through frequency division multiple access (hereinafter simply called FD-MA) using signals in the voice band. Of the bandwidth of 6 MHz assigned to telephone services, the usable frequency band (hereinafter called a use-band) is set to 2.5 MHz or narrower in order to avoid interference with television broadcast. The use-band has 200 carriers (channels) at the maximum, a frequency interval being defined to be an integer multiple of 12.5 MHz which is a narrow bandwidth of an FM transceiver. These technical requirements are stipulated in the proposals given by "Survey and Study Group for Propagation and Promotion of Highly Integrated Information and Communication Systems".

Each of 200 channels for telephone services has a control channel and a speech channel. The control channel is used for digital switch control, and the speech channel is used for transmitting a speech signal through analog frequency division multiplex. Telephone communications between subscribers are established via the head end (base station). In telephone communications, an up-line signal frequency is converted by a converter at the head end into a down-line signal frequency. Connection between telephone subscribers is controlled by

designating a carrier frequency as a cross point.

Fig. 5 is a block diagram showing an example of an MCA/C system operating on shared parts of the facilities of a CATV system. In Fig. 5, reference numeral 1 represents a head end as a base station which locates at the central service area of the CATV system. A plurality of trunk cables 2a to 2d extend from this head end 1 to each route.

The head end 1 is installed with an input/output distributor 1-1 which is a branch/connection unit for the trunk cables 2a to 2d. Connected to the distributor 1-1 are a CATV broadcasting facility 1-2 and a block converter (or transceiver) 1-3. Via this block converter 1-3, a line controller 1-4 is connected to the distributor 1-1.

The trunk cables 2a to 2d are provided for respective routes, for example, four routes corresponding to the east, west, south, and north as in the case of Fig. 5. The route trunk cables 2a to 2d are extended through cascade connection of, for example, bi-directional repeaters 2a-1 and 2a-2. As shown in Fig. 5, a branch cable 3 is branched from the bi-directional repeater 2a-1, and further branched to subscriber terminals 4-1 and 4-2 from tap-off points 3-1 and 3-2 of the branch cable 3. The whole CATV system constitutes a tree network.

Installed at each terminal (terminal station) 4-1, 4-2 are a splitter 401, a television receiver 402, a line termination equipment 403, a telephone 404, and other equipments. Reception of multi-channel television broadcast as well as CATV service area communications by telephones or the like similar to wire broadcast telephones, can be performed. For the service area communications, bi-directional communications are performed using an up-line from a subscriber to the head end and a down-line from the head end to a subscriber.

The line termination equipment 403 executes a call and connection establishment operation of the MCA/C system through line control and data transfer. The line termination equipment 403 also performs signal conversion between a CATV RF signal and a terminal AF signal, and requests a call, upon reception of a callee dial number signal inputted from a terminal, by converting it and transmitting the converted signal to the line controller 1-4.

A low split scheme is prevailing as a CATV channel allocation, in which the up-line band is set to 10 to 50 MHz and the down-line band is set to 70 to 300 MHz or 450 MHz. In the MCA/C system, of these bands, the up-line band is set to 6 MHz, for example, from 42 to 48 MHz, and the down-line band is also set to 6 MHz, for example, from 230 to 236 MHz. As stated earlier, the use-band is set to 2.5 MHz or narrower with 200 channels at the maximum.

This system is called an MCA/C system because it is assumed to operate on a CATV system. However, it is not necessarily required to configure a signal transfer system by using cables. Therefore, the communication system of multi-channel access is generally called an

MCA system.

Fig. 6 is a schematic diagram illustrating the concept of multiple communication lines of the above-described MCA/C system. C-u1 and C-u2 represent up-line control channels, S-u1 and S-u2 represent up-line speech channels, C-d1 and C-d2 represent down-line control channels, and S-d1 and S-d2 represent down-line speech channels. As illustrated by broken lines, the block converter 1-3 converts each up-line use-band into a corresponding down-line use band.

In the diagram of Fig. 6 illustrating the concept of multiple communication lines, a plurality of up- and down-line communication lines are depicted in order to facilitate the description of line connections. However, actually, bi-directional communications over a plurality of different up- and down-line channels are realized by a single communication cable (such as branch cable 3) through frequency division multiplex transmission. Different communication channel lines shown in Fig. 6 correspond to different frequencies. Also in Fig. 6, each communication channel line intersects with two lines extended from the line controller 1-4 or line termination equipment 403. These virtual cross points each are closed when the line termination equipment 403 sets a channel line corresponding to the frequency designated by the line controller 1-4. The virtual cross points are not physical points but logical points. A white circle cross point indicates that a communication channel between the line controller or line termination equipment and the block converter is opened. A solid black cross point indicates that the line controller or line termination equipment is connected to the communication channel. Such line connection operations are controlled by designating or selecting a channel frequency.

It is assumed that the subscriber terminal 4-1 is a caller and the subscriber terminal 4-2 is a callee. First, the caller 4-1 transmits a signal having the frequency of the control channel C-u1 so that the virtual cross point a is closed and a connection request signal containing a callee dial number is transmitted over the control channel C-u1.

Then, the line controller 1-4 at the head end 1 receives this connection request signal because the frequency of the control channel C-u1 is used and so the virtual cross point b is closed. Thereafter, a connection response signal is transmitted over the control channel C-d2 because the frequency of the control channel C-d2 is next used and so the virtual cross point c is closed.

Next, the caller and callee close the virtual cross points d and e to receive this signal, and then speech communications start using the speech channel designated by the line controller 1-4. Specifically, on the caller 4-1 side, the virtual cross point f is closed to speak over the speech channel S-u1, and on the callee 4-2 side, the virtual cross point g is closed to receive a speech signal sent from the caller over the speech channel S-d1 via the block converter 1-3. Then, the virtual cross point h is closed so that the callee 4-2 can speak over

the speech channel S-u2. On the caller 4-2 side, the virtual cross point i is closed to receive a speech signal sent over the speech channel S-d2. In this manner, simultaneous bi-directional transmission/ reception becomes possible.

In the above description, although frequency division multiplex is used, it is obvious that other multiplex accesses such as time division multiplex and code division multiplex are also applicable.

In communication systems of multi-channel access, there is a system having a so-called group call function in which a plurality of terminals such as subscribers 4-1, 4-2 are classified into groups with some terminals belonging to a plurality of groups, and terminals can be called in the unit of group. Such a system can utilize the multi-channel access function more effectively.

Such a group call function is used for services such as communications (broadcast) of a single subscriber terminal with a plurality of subscriber terminals and communications (e.g., conference via communication channels) between a plurality set of terminals and another plurality set of terminals.

In a conventional system having such a group call function, however, a group call is acknowledged if only it is judged that this group is not in communications with another terminal or group.

Specifically, in using the group call function, this conventional system does not consider the case where some terminals among a plurality of terminals of the system belong to a plurality of groups in an overlap manner. Therefore, some terminals in the called group cannot be accessed if the terminals are in communications with another terminal or group.

Consider for example the case where as shown in Fig. 2, a plurality of terminals A, B, C, D, E, F, and G are classified into groups 1 and 2 and the terminals D and E belong to both the groups 1 and 2. It is assumed that while the group 1 is communicating with the other terminal (or group) X, i.e., while the terminals A, B, C, D, and E are communicating with the terminal (or group) X, another terminal (or group) Y calls the group 2 as shown in Fig. 3. In Fig. 3, the slant hatching indicate the communicating terminals, and while no hatching indicate terminals in no communication. In this case, since the group 2 is not communicating with the terminal (or group) X, the base station (head end) transmits a call signal via the control channel to the terminals D, E, F, and G in the group 2.

Therefore, although the terminals F and G among the terminals belonging to the group 2 receive this call signal and start communicating with the terminal (or group) Y, the terminals D and E of the group 2 cannot receive the call signal from the terminal (or group) Y because they are in communications with the terminal (or group) X, and continue the communications of the group 1 with the terminal (or group) X as shown in Fig. 4. In Fig. 4, every terminal of group 1 is communicating with the other terminal X, and while the terminals F and G of

group 2 are communicating with the other terminal Y. The terminals D and E of group 2 are not communicating with the terminal Y.

Accordingly, if some groups belong to a plurality of groups in an overlap manner, the terminals in one group in communications with one terminal or group cannot participate in new group communications.

Also in this case, a new group communication caller is not informed about a presence of terminals not participated in the group communications. In communications, particularly in broadcast communications in which a caller broadcasts a message to all terminals of a group, some terminals may be unable to receive the broadcast message and the caller cannot be informed of this fact.

Preferably, it is an object of the present invention to provide a communication system of multi-channel access, capable of providing a reliable group call function at any time even if there are some terminals belonging to a plurality of groups of the communication system and strictly eliminating any possibility of terminals left un-called during a group call.

The above object can be achieved by a provision of means for supervising a communication state of terminals belonging to each group. This means is used for invalidating a group call if the group has any terminal in communications with another group.

If a group has any terminal in communications, the call to the group is invalidated so that the group call function becomes valid only when all the terminals of the group are on standby. Accordingly, there is no terminal not participated in group communications when a group call is made valid.

Further aspects and advantageous features of the invention are set out in the appended claims.

Figs. 1A and 1B are data tables used by a communication system of multi-channel access according to an embodiment of the invention;

Fig. 2 is a diagram illustrating terminals belonging to two groups;

Fig. 3 is a diagram illustrating a group call according to an embodiment of the invention;

Fig. 4 is a diagram illustrating a group call according to a conventional method;

Fig. 5 is a block diagram illustrating a communication system of multi-channel access to be applied to the present invention;

Fig. 6 is a schematic diagram illustrating the concept of a communication system of multi-channel access to be applied to the present invention;

Fig. 7 is a flow chart of the group management function executed by the line controller 4-1; and

Fig. 8 is a block diagram of the line controller 1-4.

A communication system of multi-channel access according to an embodiment of the invention will be detailed with reference to the accompanying drawings.

The main structure of a communication system of multi-channel access of this invention is the same as that described with Figs. 5 and 6, and the different point is the control by the line controller 1-4 of the head end (base station) 1.

The control by the line controller 1-4 according to the embodiment of this invention will be described.

Fig. 8 is a block diagram of the line controller 1-4. The line controller 1-4 includes a CPU 101, a data transmission/reception unit 102, a modem 103, a RF transmitter/receiver unit 104, ROM 105 and RAM 106 which are connected together with a bus line and signal lines.

The line termination equipment 403 makes the line controlling and data transmission/reception to operate the calling and incoming of MCA/C and the communication under the controlling by the line controller 1-4.

Upon the user's operation, the line termination equipment 403 at the transmission side transmits a calling request to the line controller 104 of the head end 1. When the calling request is acceptable, the line controller 1-4 transmits a channel designation to both of the line termination equipments 403 at the transmission side and the reception side.

Each of the line termination equipments 403 of the transmission side and the reception side shifts its channel (frequency) to the other one designated by the channel designation from the line controller 1-4. As the result, the virtual cross points are closed to make the communication available to start between the line termination equipments 403 of the transmission side and the reception side.

In this embodiment, the line controller 1-4 is provided with a group management function for supervising a communication state of terminals (4-1,...) of each group and storing, in a table shown in Fig. 1, management information on whether each terminal belonging to groups in an overlapped manner. This group management function is executed by the CPU 101 according to the software program stored in the ROM 105.

The table shown in Fig. 1A is assumed that the number of groups in the system is five. In the table, "1" (overlapped) is set if there is a terminal in communications among the terminals belonging to multiple groups, and "0" (not overlapped) is set if there is no terminal in communications among the terminals belonging to multiple groups. For example, group 1 has the communication terminals belonging to the other groups 2 and 3, and has no terminals belonging to the groups 4 and 5.

Fig. 1B is another table which indicates the status of communication in each of the groups 1-5. In the communication management table shown in Fig. 1B, when x at a certain group is "1", this group is communicating with the other group or terminal, and when x is "0", the group is not communicating with any other group or terminal. These tables shown in Figs. 1A and 1B are managed by the line controller 1-4.

When a terminal calls a group, for example, the group 2, the group supervising function of the line con-

troller 1-4 checks the row of the group 2 of the tables shown in Figs. 1A and 1B.

Fig. 7 is a flowchart of the group management function executed by the line controller 4-1. When a group call request is received at the line controller 1-4, the present status of the called group is checked by looking up the table of Fig. 1B at step 201. When the table of Fig. 1B indicates that the called group is communicating ($x=1$) with the other group or terminal (step 202), the group call request is made invalid. (step 207) When the table of Fig. 1B indicates that the called group is not communicating ($x=0$) with the other group or terminal (step 202), another table shown in Fig. 1A is checked. (step 203) If the called group includes the overlapped terminals belonging to the other groups, the present status of the such other groups is checked by looking up the table of Fig. 1B at step 205. When the table of Fig. 1B indicates that the other groups are not in communicating status ($x=0$) at step 206, the group call request is valid and executed.

In the example of the table shown in Fig. 1A, the group 2 is overlapped with the groups 1 and 5.

In this example, the group supervising function of the line controller 1-4 invalidates a call to the group 2 if there is even one terminal in communications in the groups 1 and 5, and informs the caller of the group 2 of an invalid call.

A notice of this invalid call may be performed, for example, by sending a busy tone like a telephone line back to the caller.

Consider, for example, the case shown in Fig. 2 where there are a group 1 with terminals A, B, C, D, and E and a group 2 with terminals D, E, F, and G. In this case, not only if the group 1 is in group communications, i.e., if all terminals A, B, C, and D are in communications, but also if even one terminal is in communications during a group idle state of the group 1, then a call to the group 2 is invalidated. As a result, the group call request is invalid, however in the terminals belonging to the group 2, only the terminals D and E belonging to both the groups 1 and 2 are absolutely protected from an inability of participating in the communications to the group 2 (an inability of listening to the broadcast).

As already described with Figs. 5 and 6, signal transmission lines such as trunk cables 2a to 2d and the branch cable 3 of the communication system of multi-channel access applied to this invention are made of coaxial cables through which high frequency electric signals are transmitted to send information. Instead of coaxial cables, optical cables may be used to form transmission lines through which high frequency optical signals are transmitted.

Signal transmission lines of the communication system of multi-channel access may be radio wave transmission lines.

Not only analog electric signals but also digital electric signals may be used for transmitting information.

As described so far, according to the present inven-

tion, if there is even one terminal in communications among those terminals belonging to a plurality of groups, a new call to all the groups having the terminal in communications is made invalid, and the caller to these groups is informed of this fact. Accordingly, it is possible to strictly eliminate an occurrence of any terminals left uncalled during a group call and to perform a reliable group call function.

Claims

1. A multi-channel access communication system for communicating between a plurality of terminals (4-1, 4-2) through a transmission medium comprises;

a plurality of terminals classified into a plurality of groups, in which at least one terminal belongs to at least two groups;

a transmission medium for transmitting control signals and information signals between said terminals; and

a base station (1) having a memory means for storing a communicating status of said terminal in said each group and a line controlling means (1-4); said line controlling means providing a group call function for calling all terminals belonging in each group and being so design as to invalidate a group call for calling all terminals in one group, in which there is at least said one terminal belonging to at least two groups when said one terminal in one group is in a communication status with other terminal and at a same time, the other group which said one terminal belongs receives said group call.

2. A multi-channel access communication system according to claim 1, wherein said transmission medium is one of a coaxial cable line for transmitting a high frequency electric signal and an optical cable line for transmitting a high frequency optical signal.

3. A multi-channel access communication system according to claim 1, wherein said transmission medium is a radio wave transmission line.

4. A multi-channel access communication system according to claim 1, wherein said memory means having a table, in which said communicating status of said terminal is stored

5. A method of calling a terminal of a multi-channel access communication system having a plurality of terminals (4-1, 4-2) connected to communication channels and classified into a plurality of groups, in which at least one terminal belongs to at least two groups, the method comprising the steps of:




European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 96 30 0653

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
A	WO 91 15932 A (MOTOROLA INC) * page 1, line 23 - page 2, line 26 *	1,3-6	H04Q7/22 H04Q7/28 H04M3/56
A	WO 94 23525 A (NOKIA TELECOMMUNICATIONS OY ; LEHMUSTO MIKA (FI)) * abstract * * page 7, line 18 - page 8, line 13; figure 1 *	1,3-6	
A	GB 2 271 690 A (MOTOROLA ISRAEL LTD) * abstract * * page 1, line 13 - page 4, line 32 *	1,3-6	
A	PATENT ABSTRACTS OF JAPAN vol. 016, no. 372 (E-1246), 11 August 1992 & JP 04 117859 A (MATSUSHITA ELECTRIC IND CO LTD), 17 April 1992, * abstract *	1,2	
The present search report has been drawn up for all claims			TECHNICAL FIELDS SEARCHED (Int.Cl.6)
			H04Q H04M
Place of search THE HAGUE		Date of completion of the search 27 November 1997	Examiner Annibal, P
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

EPO FORM 1503 (03.82) (P04C01)



(19)

Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 0 725 549 A3

(12)

EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
21.01.1998 Bulletin 1998/04

(51) Int Cl.⁶: H04Q 7/22, H04Q 7/28,
H04M 3/56

(43) Date of publication A2:
07.08.1996 Bulletin 1996/32

(21) Application number: 96300653.1

(22) Date of filing: 30.01.1996

(84) Designated Contracting States:
DE FR GB SE

(30) Priority: 02.02.1995 JP 15928/95

(71) Applicant: HITACHI DENSHI KABUSHIKI KAISHA
Chiyoda-ku, Tokyo 101 (JP)

(72) Inventors:
• Niki, Atsuyoshi
Koganei-shi (JP)


• Maeda, Ichiro
Tama-shi (JP)
• Fukushima, Takao
Hanno-shi (JP)

(74) Representative: Hackney, Nigel John et al
Mewburn Ellis,
York House,
23 Kingsway
London WC2B 6HP (GB)

(54) Group-calls in a multi-channel access communication system

(57) A method of calling a terminal of a multi-channel access communication system having a plurality of terminals (4-1, 4-2) connected to communication channels. The plurality of terminals are classified into a plurality of groups each including at least one terminal. When a group calls another group, it is checked by referring to a management table (Figs. 1A & 1B) if there is any terminal in communications in the called group. If there is a terminal in communications, the call is invalidated.

FIG.7



EP 0 725 549 A3

FIG.8




FIG.7




FIG. 6




FIG. 5




FIG.3




FIG.4




FIG.1A

	GROUP1	GROUP2	GROUP3	GROUP4	GROUP5
GROUP1	1	1	1	0	0
GROUP2	1	1	0	0	1
GROUP3	1	0	1	1	0
GROUP4	0	0	1	1	0
GROUP5	0	1	0	0	1

1: OVERLAPPED

0: NOT OVERLAPPED


FIG.1B

GROUP 1	x
GROUP 2	x
GROUP 3	x
GROUP 4	x
GROUP 5	x

x = 1 : COMMUNICATING

x = 0 : NOT COMMUNICATING

FIG.2



calling (200) one of the groups;
judging (201 - 206) if there is said one terminal
in communications in the called group; and
issuing (207) a notice of an invalid call, when
there is said one terminal in communications.

5

6. A method according to claim 5, wherein the judgement step identifies the called group, identifies another group having an overlapped terminal belonging also to the called group by referring to a group management table (Figs. 1A & 1B), judging if the other group having the overlapped terminal is in communications, and if the other group is in communications, judging that there is a terminal in communications.

10

15

20

25

30

35

40

45

50

55

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☒ FADED TEXT OR DRAWING
- ☒ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☐ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.